

ELECTRONIC FLUORESCENT BALLASTS FOR MULTIPLE LIGHTING APPLICATIONS

Fluorescent

10 ballasts operate 132 lamps
in 860 combinations
Fluorescent T5 ultra-slim type
2 ballasts operate 41 lamps
in 70 combinations

FEATURES: solid state, high power factor,
small case sizes, lightweight, energy savings,
longer lamp life, versatile, 120 & 277 volts



APPLICATIONS: T2-T5-T6-T8-T10-T12-Biax-Flat Quads,
Triple Biax-2D-Circline-HO's-VHO's-HID's

Too many types to list. For correct ballast application please follow our 4 easy steps

1. lamp description 2. number of lamps 3. voltage used 4. call 800 445 6611

WORKHORSE BALLASTS

L = Long C = Cube or Square

MODEL	BW1L	BW2C	BW22C	BW3C	BW33C
		BW2C277	BW22C277	BW3C277	
	BW1L277	BW2L	BW22L	BW3L	BW33L
		BW2L277	BW22L277	BW3L277	
Maximum Power 28Watts Model No. WH1-120-L Maximum Current (120vac) .20 AMP Model No. WH1-277-L Maximum Current (277vac) .11 AMP Black/White Wires - 12 in. Red/Yellow Wires - 24 in. Ballast Case Size - 120-L (H .75", W 1", L 7.5") Ballast Case Size - 227-L (H .75", W 1", L 7.5") Ballast Wt. - 4.5 oz. Case Qty. & Wt. - 50 pcs. 15 lbs.	Maximum Power 35Watts Model No. WH2-120-L, WH2-120-C (BLS) Maximum Current (120vac) .33 AMP Model No. WH2-277-L, WH2-120-C (BLS) Maximum Current (277vac) .15 AMP Black/White Wires L-18" C-12" Red/Yellow Wires L-38" C-12"	Maximum Power 35Watts Model No. WH22-120-L, WH22-120-C (BLS) Maximum Current (120vac) .33 AMP Model No. WH22-277-L, WH22-120-C (BLS) Maximum Current (277vac) .15 AMP Black/White Wires L-18" C-12" Red/Yellow Wires L-38" C-12"	Maximum Power 35Watts Model No. WH22-120-L, WH22-120-C (BLS) Maximum Current (120vac) .33 AMP Model No. WH22-277-L, WH22-120-C (BLS) Maximum Current (277vac) .15 AMP Black/White Wires L-18" C-12" Red/Yellow Wires L-38" C-12"	Maximum Power 64Watts Model No. WH3-120-L, WH3-120-C (BLS) Maximum Current (120vac) .56 AMP Model No. WH3-277-L, WH3-120-C (BLS) Maximum Current (277vac) .24 AMP Black/White Wires L-18" C-12" Red/Yellow Wires L-38" C-12"	Maximum Power 64Watts Model No. WH33-120-L Maximum Current (120vac) .53 AMP Model No. WH33-120-C (BLS) Maximum Current (277vac) .56 AMP Black/White Wires L-18" C-12" Red/Yellow Wires L-38" C-12" Case L = H 1", W 1.5", L 6.5" C = H 1", W 3.1", L 3.82" Ballast Wt. - 10 oz. Case Qty. & Wt. - 50 pcs. 32 lbs.
	Case L = H 1.25", W 1", L 5.5" C = H 1", W 1.75", L 3.3" Ballast Wt. - 7 oz. Case Qty. & Wt. - 50 pcs. 22 lbs.	Case L = H 1.25", W 1", L 5.5" C = H 1", W 2.3", L 3.3" Ballast Wt. - 7 oz. Case Qty. & Wt. - 50 pcs. 22 lbs.	Case L = H 1.25", W 1", L 6.5" 120 C=H 1", W 2.5", L 3.8" C = H 1", W 3.1", L 3.8" Ballast Wt. - 10 oz. Case Qty. & Wt. - 50 pcs. 32 lbs.		

USA & CANADA

1-800-445-6611

FAX: 1-800-445-6690

www.MillerLightingProducts.com



PHOENIX, AZ

Phone: 602-268-0001

Fax: 602-268-0130

customerservice@millerlightingproducts.com