

ELECTRONIC FLUORESCENT BALLASTS FOR MULTIPLE LIGHTING APPLICATIONS

Too many types to list. For correct ballast application please follow our 4 easy steps

1. lamp description 2. number of lamps 3. voltage used 4. call 800 445 6611

WORKHORSE BALLASTS

L = Long C = Cube or Square

MODEL	BW4L	BW5L	BW6L	BW7L	BW8L
	BW4L277	BW5L277	BW6L277	BW7L277	BW8L277
	Maximum Power 70Watts Model No. WH4-120-L Maximum Current (120vac) .56 AMP Model No. WH4-277-L Maximum Current (277vac) .24 AMP Black/White Wires - 18 in. Red/Yellow Wires - 36 in. Ballast Case Size - 120-L (H 1",W 1.5", L 6.5") Ballast Wt. - 10 oz. Case Qty. & Wt. - 50 pcs. 32 lbs.	Maximum Power 128Watts Model No. WH5-120-L Maximum Current (120vac) 1.15 AMP Model No. WH5-277-L Maximum Current (277vac) 0.48 AMP Black/White Wires L-18" Red/Yellow Wires L-36" Case 120 L= H 1",W 1.72", L 8.5" L = H 1",W 1.72", L 9.5" Ballast Wt. - 14 oz. Case Qty. & Wt. - 50 pcs. 44 lbs.	Maximum Power 140Watts Model No. WH6-120-L Maximum Current (120vac) 1.04 AMP Model No. WH6-277-L Maximum Current (277vac) 0.50 AMP Black/White Wires 18" Red/Yellow Wires 36" Case 120 L = H 1",W 1.72", L 8.5" 277 = H 1",W 1.72", L 9.5" Ballast Wt. - 15 oz. Case Qty. & Wt. - 50 pcs. 47.5 lbs.	Maximum Power 220Watts Model No. WH7-120-L Maximum Current (120vac) 1.82 AMP Model No. WH7-277-L Maximum Current (277vac) .85 AMP Black/White Wires 18" Red/Yellow Wires 36" Case L = H 1",W 1.72", L 18.25" Ballast Wt. - 32.8 oz. Case Qty. & Wt. - 25 pcs. 57 lbs.	Maximum Power 220Watts Model No. WH8-120-L Maximum Current (120vac) 1.8 AMP Model No. WH8-277-L Maximum Current (277vac) .74 AMP Black/White Wires 18" Red/Yellow Wires 36" Case = H 1",W 1.72", L 18.25" Ballast Wt. - 34 oz. Case Qty. & Wt. - 25 pcs. 57 lbs.

Fluorescent

10 ballasts operate 132 lamps
 in 860 combinations
 Fluorescent T5 ultra-slim type
 2 ballasts operate 41 lamps
 in 70 combinations

FEATURES: solid state, high power factor, small case sizes, lightweight, energy savings, longer lamp life, versatile, 120 & 277 volts



APPLICATIONS: T2-T5-T6-T8-T10-T12-Biax-Flat Quads, Triple Biax-2D-Circline-HO's-VHO's-HID's

USA & CANADA

1-800-445-6611

FAX WATS 1-800-445-6690

www.MillerLightingProducts.com



PHOENIX, AZ

Phone: 602-268-0001

Fax: 602-268-0130

customerservice@millerlightingproducts.com